



BEAMZ
MADE
EAZY

153.301 V3.1

BS1500W CW

QUICK START GUIDE

CONTROL MENU

MENU			DESCRIPTION
DMX ADDR	001-512		DMX address setting
CHANNEL	4/12/16		Select DMX channel mode
AUTO RUN	0-39	000-255	Auto program and speed adjustment
EFFECT ON AUTO	Dimmer	000-255	Adjust dimmer level and switch on strobe at different speed for auto run
	Strobe	000-255	
MONITOR	Channel 4 mode		Checking DMX values for each DMX Channel
	Channel 12 mode		
	Channel 16 mode		
BACK L	on		Display background light always stays on
	60s		Display background light turns off after 60s
	120s		Display background light turns off after 120s
	300s		Display background light turns off after 300s
TEMP	Temp	xx°C	Display current temperature on LED panel
INFO	Test1		Test mode without flash
	Test2		Test mode with flash
	Reset	Yes No	Restore factory settings
	Version	Vxx	Display current version

DMX CHANNELS

4 CHANNELS


CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-015	No function
		016-255	Dimmer 0-100%
2	Strobe	000-002	No function
		003-255	Beam flash intensity, from slow to fast
3	Special effect	000-003	No function
		004-255	Choose between several effects
4	Speed of effect	000-255	Speed of special effect from channel 3

12 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Section 1	000-255	Dimmer 0-100%
2	Section 2	000-255	Dimmer 0-100%
3	Section 3	000-255	Dimmer 0-100%
4	Section 4	000-255	Dimmer 0-100%
5	Section 5	000-255	Dimmer 0-100%
6	Section 6	000-255	Dimmer 0-100%
7	Section 7	000-255	Dimmer 0-100%
8	Section 8	000-255	Dimmer 0-100%
9	Section 9	000-255	Dimmer 0-100%
10	Section 10	000-255	Dimmer 0-100%
11	Section 11	000-255	Dimmer 0-100%
12	Section 12	000-255	Dimmer 0-100%

16 CHANNELS

CHANNEL	FUNCTION	VALUE	DESCRIPTION
1	Dimmer	000-255	Master dimmer 0-100%
2	Strobe	000-255	Beam flash intensity, from slow to fast
3	Special effect	000-255	Choose between several effects
4	Speed of effect	000-255	Speed of special effect from channel 3
5	Section 1	000-255	Dimmer 0-100%
6	Section 2	000-255	Dimmer 0-100%
7	Section 3	000-255	Dimmer 0-100%
8	Section 4	000-255	Dimmer 0-100%
9	Section 5	000-255	Dimmer 0-100%
10	Section 6	000-255	Dimmer 0-100%
11	Section 7	000-255	Dimmer 0-100%
12	Section 8	000-255	Dimmer 0-100%
13	Section 9	000-255	Dimmer 0-100%
14	Section 10	000-255	Dimmer 0-100%
15	Section 11	000-255	Dimmer 0-100%
16	Section 12	000-255	Dimmer 0-100%





BEAMZ

**YOUR FUTURE
YOUR SKILLS
YOUR PLATFORM
YOUR PARTY
YOUR EVENT**



offers a wide range of high performance lighting equipment and related accessories for the rental, entertainment and architectural lighting markets. BeamZ Pro stands for performance, innovation and value pricing!

