



FASTER 384

Product Code: SG FASTER384

DMX controller for scanner and moving head 384 CH



Description

Faster384 is a simple and intuitive control unit for scanners and motorised devices. Faster384 is a compact-sized DMX controller, designed to manage up to 12 projectors with operation up to 32 channels each. The control unit lets you customise programs and internal settings and store up to 240 scenes and 6 chases on 30 different banks.

Technical Specifications

Technical data

- DMX controller
- Max 12 projectors, 32 channel each
- Total 384 DMX channels
- 8 sliders for control (page A/B)
- 8 programmable scenes in 30 banks
- 6 chases
- Auto mode
- Sound mode (internal microphone)

Power supply

- Input Voltage: DC 12V, 300 mA min
- External adapter included: AC~100-240V, 50/60Hz

Weight and dimensions

- Net weight: 2,5 kg
- Dimensions: 482x132x80 mm